











Instruction Sheet

Subject: Performing an FIB 2 Reset to reset filter lockout or AM/PM filter.

Models affected: FilterQuick Touch Fryers with FQ4000 controllers

DISPLAY	ACTION
 	1. With ALL the controllers at the off/standby position, press the Home button.
	2. Press the Service button.
	3. Press the Service button.
3 0 0 0	4. Enter 3000
	5. Press the √ (check) button.
	6. Press the Down arrow button.
FIB - RESET 2	7. Press the FIB - RESET 2 button.
CONFIRM? YES NO	8. Press the YES button.
FIB 2 RESET IN PROGRESS RESET COMPLETED SUCCESSFULLY	9. No action.
	10. Press the √ (check) button.
	11. Press the Home button.
 CREW MODE	12. Press the Crew Mode button.
	13. Press and hold the power switch to turn on fryers. Once at setpoint, press the FILTER BUTTON to filter if necessary.