










# Instruction Sheet

**Subject: Performing an FIB 2 Reset to reset filter lockout or AM/PM filter.**

**Models affected: FilterQuick Touch Fryers with FQ4000 controllers**

DISPLAY	ACTION
	1. With ALL the controllers at the off/standby position, press the Home button.
	2. Press the Service button.
	3. Press the Service button.
<b>3 0 0 0</b>	4. Enter <b>3000</b>
	5. Press the √ (check) button.
	6. Press the Down arrow button.
<b>FIB - RESET 2</b>	7. Press the FIB - RESET 2 button.
<b>CONFIRM? YES NO</b>	8. Press the YES button.
<b>FIB 2 RESET IN PROGRESS RESET COMPLETED SUCCESSFULLY</b>	9. No action.
	10. Press the √ (check) button.
	11. Press the Home button.
 <b>CREW MODE</b>	12. Press the Crew Mode button.
	13. Press and hold the power switch to turn on fryers. Once at setpoint, press the FILTER BUTTON to filter if necessary.